



- ✓ Reduced size.
- ✓ Built-in FM exciter.
- ✓ LDMOS latest technology transistors.
- ✓ Overall efficiency over 79%.
- ✓ Power Stage efficiency over 82%.
- ✓ Minimum energy consumption.
- ✓ Custom design.
- ✓ Stereo coder and RDS encoder also built-in (optional).
- ✓ Remote monitoring from computer and mobile phone (optional).



# COMPACT series

## FM Transmitter 3KW

Frequency band	87.5 - 108MHz
Frequency step	100KHz step
Output power	0 to 3KW adjustable.
Output connector	EIA 7/8" FLANGE
Output impedance	50Ω
Modulation capability	±350KHz
Harmonics and spurious	Complies with CCIR and FCC.
Audio inputs	MPX/Mono input, selectable from the menu
Modulation	F3E ±75KHz
FM S/N	Better than -88dB (75KHz @ 400 Hz @ 50µs pre-emphasis)
AM S/N	Better than -60dB
Spurious radiation	<-70dB.
Storage temperature	0°C a +45°C
Relative humidity	90% RH, non-condensing
Altitude	4000m
Supply	230VAC Mono-phase, 230/380VAC Three-phase, 50/60Hz.
Consumption	3900VA typical.
Dimensions	W 483 (19") x H 266 (6U) x D 670mm

ISO 9001  
BUREAU VERITAS  
Certification



Features and specifications are subject to change without notice.



**Seratel Technology**

Calle Trópico, 6A • Bajo • Edificio Trópico  
28850 Torrejón de Ardoz • Madrid • España  
Tel. (34) 916 567 565 • Fax (34) 916 566 80  
seratel@seratel.com • www.seratel.com