



- ✓ LDMOS latest technology transistors.
- ✓ Minimum energy consumption.
- ✓ Custom design.
- ✓ Stereo coder and RDS encoder also built-in (optional).
- ✓ Remote monitoring from computer and mobile phone (optional).

COMPACT series

75W FM Transmitter

Frequency band	87.5 - 108MHz
Frequency step	100KHz step
Output power	0 to 75W adjustable.
Output connector	N
Output impedance	50Ω
Modulation capability	±350KHz
Harmonics and spurious	Complies with CCIR and FCC.
Audio inputs	MPX/Mono input, selectable from the menu
Modulation	F3E ±75KHz
FM S/N	Better than -88dB (75KHz @ 400 Hz @ 50μs pre-emphasis)
AM S/N	Better than -60dB
Spurious radiation	<-70dB.
Storage temperature	0°C a +45°C
Relative humidity	90% RH, non-condensing
Altitude	4000m
Supply	230VAC.
Dimensions	W 483 (19") x H 88 (2U) x D 370mm

ISO 9001
BUREAU VERITAS
Certification



Seratel Technology
Calle Trópico, 6A • Bajo • Edificio Trópico
28850 Torrejón de Ardoz • Madrid • España
Tel. (34) 916 567 565 • Fax (34) 916 566 80
seratel@seratel.com • www.seratel.com